

2. Horn System

A: WIRING DIAGRAM


1. HORN

<Ref. to WI-123, WIRING DIAGRAM, Horn System. >

B: INSPECTION

1. HORN RELAY

Measure the security horn relay resistance between terminals (indicated in the table below) when connecting terminal No. 4 to battery positive terminal and terminal No. 3 to battery ground terminal.



Current	Terminal No.	Standard
Yes	1 and 2	Less than 1 Ω
No		1 MΩ or more